



Polyethylene

Borlink™ LE0595

Crosslinkable Semiconductive Compound

Description

Borlink LE0595 is a crosslinkable black polyethylene compound, specially designed for semiconductive conductor screen and bonded insulation screen of energy cables.

Applications

Borlink LE0595 is designed for semiconductive screens in XLPE medium and high voltage cables. It can be used as inner and outer screen for bonded cable construction and as inner screen for strippable cable constructions.

Specifications

Borlink LE0595 meets the applicable requirements as below when processed using sound extrusion practices and testing procedures

AEIC CS8	IEC 60840
AEIC CS9	ICEA S-93-639
BS 6622	ICEA S-94-649
DIN VDE 0276-263	ICEA S-97-682
DIN VDE 0276-620	ICEA S-108-720
Cenelec HD 620 S1	NF C33-223
Cenelec HD 632 S1	NF C33-226
IEC 60502-2	UTE C 33-223

Special Features

Borlink LE0595 is a ready-to-use semiconductive compound. It offers excellent thermal stability which provides robust cable extrusion and crosslinking at high surface temperature, allowing for high line speed.

The excellent distribution of carbon black and additives in Borlink LE0595 results in a smooth semiconductive screen.

Physical Properties

Property	Typical Value	Test Method
Data should not be used for specification work		
Density	1135 kg/m ³	ISO 1183
Tensile Strain at Break (25 mm/min) ¹	200 %	ISO 527
Tensile Strength (25 mm/min) ¹	22 MPa	ISO 527
Change of Tensile Properties After Ageing (168 h, 135 °C) ¹	< 20 %	IEC 60811-401
Hot Set Test (200 °C, 0,20 MPa)	Elongation under load 25 % Permanent deformation 0 %	IEC 60811-507
MDR, max torque	12,0 dNm	ISO 6502
Moisture	200 ppm	Karl Fischer-titration

¹ Measured on crosslinked specimens





Polyethylene Borlink LE0595

Electrical Properties

Property	Typical Value <small>Data should not be used for specification work</small>	Test Method
DC Volume Resistivity (23 °C)	< 100 Ωcm	ISO 3915
DC Volume Resistivity (90 °C)	< 1000 Ωcm	ISO 3915

Processing Techniques

Borlink LE0595 provides excellent surface finish and outstanding output rates, when processing conditions are optimized for the actual processing equipment and cable dimensions. Optimal conditions may vary according to the equipment used. To produce a good and reliable cable, it is essential to ensure careful and very clean handling of the semiconductive material.

Hence all material handling should preferably be conducted in closed systems. Please contact your Borealis representative for more details.

Extrusion

Typical processing temperature ranges for **Borlink LE0595** are shown below:

Hopper drying (4 h)	60 °C	With dehumidified air
Melt temperature	120 - 135 °C	

Packaging

Package:	Octabins Smallbins
----------	-----------------------

Storage

Borlink LE0595 has a shelf life of 18 months from production date if stored in unopened original packages, under dry and clean conditions at temperatures between 10 - 30 °C (50 - 85 °F).

More information on storage is found in our "Safety data sheet" / "Product safety information sheet" for this product.

Safety

Please see our "Safety data sheet" / "Product safety information sheet" for details on various aspects of safety of the product. For more information, contact your Borealis representative.





Polyethylene Borlink LE0595

Disclaimer

The product(s) mentioned herein are not intended to be used for medical, pharmaceutical or healthcare applications and we do not support their use for such applications.

To the best of our knowledge, the information contained herein is accurate and reliable as of the date of publication; however we do not assume any liability whatsoever for the accuracy and completeness of such information.

Borealis makes no warranties which extend beyond the description contained herein. Nothing herein shall constitute any warranty of merchantability or fitness for a particular purpose.

It is the customer's responsibility to inspect and test our products in order to satisfy itself as to the suitability of the products for the customer's particular purpose. The customer is responsible for the appropriate, safe and legal use, processing and handling of our products.

No liability can be accepted in respect of the use of any Borealis product in conjunction with any other products and/or materials. The information contained herein relates exclusively to our products when not used in conjunction with any other material unless as specifically provided for in the test methods stated above.

